

# rond 2.0 big trim socket type E / F



**socket specs**

<b>application</b>	16A / 250V
<b>flush-mounting depth</b>	40 mm
<b>wire stripping length</b>	13.8 mm
<b>wire capacity</b>	up to 4 x 2.5 mm <sup>2</sup> per terminal
<b>wire fixation</b>	screw terminals (TX8)
<b>ambient temperature</b>	-5 till +40°C
<b>IP, IK rating</b>	IP21-D    IK06
<b>marking</b>	CE

**accessories**

**installation**

<b>8800 - 2015</b>	big trim holder
<b>8800 - 2010</b>	removal tool

**order number**

	type E		type F	
	black cup	white cup	black cup	white cup
<b>cover ring</b>				
<b>basic black</b>	8800 - 2166	-	8888 - 9068	-
<b>basic white</b>	-	8800 - 2167	-	8888 - 9069
<b>black ano</b>	8800 - 2168	-	8888 - 9070	-
<b>white alu</b>	-	8800 - 2169	-	8888 - 9071
<b>brushed nickel</b>	8800 - 2176	8800 - 2170	8888 - 9078	8888 - 9072
<b>brushed brass</b>	8800 - 2177	8800 - 2171	8888 - 9079	8888 - 9073
<b>light bronze</b>	8800 - 2178	8800 - 2172	8888 - 9080	8888 - 9074
<b>dark bronze</b>	8800 - 2179	8800 - 2173	8888 - 9081	8888 - 9075
<b>canon de fusil light</b>	8800 - 2180	8800 - 2174	8888 - 9082	8888 - 9076
<b>canon de fusil dark</b>	8800 - 2181	8800 - 2175	8888 - 9083	8888 - 9077